

# **MIL-LEDPWR**

**RGB Control Module** 









## **Table of Contents**

**Product Description Mounting Location** 

8

9

Installation **Daisy Chain** 

**Troubleshooting** 

Some Lights Working	1.	Check RGB settings	1.	See stereo manual
	2.	Check speaker cables.	3.	Ensure cables are correctly spliced with corresponding cables and check for crimping on top of wire insulation.
	3.	Check terminals inside of Molex connectors		
	4.	Improperly seated connection		Ensure some did not back out. Push back in until a click is felt. Pull to test to make sure they will stay in. If not, replace the affected pigtail
	5.	Defective speaker		
			4.	Ensure all cables are properly seated in correct LEDPWR outlets.
			5.	Swap non-working speaker with a working speaker to verify that the lights inside the speaker are working. Replace speaker if no.

### **Product Description**

This power module (part MIL-LEDPWR) was specifically designed to work in tandem with the Infinity by Harman marine stereo models, REFPRV415 and KAPPRV515. Once the MIL-LEDPWR is connected to the stereo, RGB speakers can connect to this power module with the end result being able to control the lighting of the speakers through the stereo.

Suggested RGB speaker models to complement this power module include:

- -JBL Club marine and JBL Stadium marine lineup
- -Infinity Reference and Infinity Kappa marine lineup

For further info on our products, please go to www.prospecelectronics.com.

Prospec Electronics is based out of Mount Pleasant, S.C. and is the home of

JBL by Harman and Infinity by Harman marine audio products.

10

#### **Mounting Location**

- 1. Choose the mounting location carefully so that the unit will not interfere with the normal driving functions of the boat or side by side vehicle.
- 2. Install the box in a dry area and with the wire end facing down as noted on the box.
- Only use the supplied mounting hardware for a safe and secure installation.



Note: Each added speaker will contribute to the overall operating current of the LEDPWR. Generally, if the RGB lights of a speaker draws 100 ma, the overall operating current of the LEDPWR will increase by that amount. For example, the operating current with no speakers attached is approximately 15ma. If two speakers with a rating of 100ma each are added, the overall operating current will increase to approximately 215ma, give or take. Not to worry, powering the stereo off will also power down the LEDPWR and reduce the current to a negligible 3.5ma.

#### **Troubleshooting**

Issue	Cause	Solution	
No LED Lights Working	RGB settings on radio too low	See stereo user manual	
	Improperly wired. (Note: Improperly matched wires can	Ensure speaker cables are spliced so colors correspond	
	cause permanent damage to the LEDPWR	Ensure RGB cable from stereo is plugged into the outlet on the	
	Incorrect Outlet/Improperly Seated	LEDPWR labeled "Head Unit Connection" and ensure it is	
	4. Blown Fuse	properly seated	
	5. Check Power Connection	Check 15-amp fuse. Replace if blown	
		5. Measure with multimeter	

4


### **Daisy Chain**

- 1. Using two splice pigtails (same as RGB speaker cable), connect one end into the outlet labeled "RGB Box Connection" seen in the wiring diagram.
- 2. Connect the remaining end into the secondary LEDPWR box at the outlet labeled "Head Unit Connection".
- 3. Repeat above for each additional LEDPWR box.

Specs						
Dimensions 151mm (L) x 102mm (W) x 45mm (H)		Speaker Voltage	12 Volts per Port			
Operating Voltage	12VDC	Current per Speaker Output	2.5 amps RMS/5 amps Peak			
Fuse	5 Amp	Current at Rest	3.5 ma			
Head Unit Connections	1	Mating Pigtails	MIL-LEDPIGTAILM (Bulk) or MIL-LED- PIGTAILPKG4 (package of 4)			
Daisy Chain Connections	1	Pigtail Connectors	Molex MicroFit Part #43025			
Speaker Connections	9	Pigtail Mating Connectors	Molex MicroFit Park #43020			
Head Unit Input Voltage 3.3 Volts		Package Includes	MILPWR, (4 ea) MIL-LEDPIGTAILM, and (4 ea) TPA 3.0X15 mounting screws. Available at prospecelectronics.com			



8





#### Installation

- 1. RGB speaker leads must be assembled using the pigtails that arrived with your LED-PWR box and the pigtails that came with your speakers.
- 2. Simply splice the two together matching wire color for wire color as per below. Failure to match color to color will result in damage to the LEDPWR box.
- 3. Connect one end of the cable to the mating connector on the speaker. Ensure the two connectors are properly aligned before snapping them in place.
- 4. Connect the remaining end to any one of the supplied Speaker Connections on the LEDPWR box.
- 5. Ensure all wiring is correct before connecting Power wires.